Настройка телефонии на Linksys SPA 2102

Данная инструкция предполагает, что вы уже ознакомились с настройкой интернета и находитесь в интерфейсе устройства.

Настройка раздела Voice.

Во вкладке System (см. рисунок 1) в разделе System Configuration поле User Password указывается пароль для доступа к Web-интерфейсу (вводится пароль, прописанный в договоре, либо произвольный пароль):

A Division of Cisco Sy	iys stems, Inc.	Linksys Phone Adapter Cor	nfiguration
Router	Voice		
Info System SIP Pro	ovisioning Region	nal Line 1 Line 2 User 1 User 2 User Login	<u>basic</u> advance
System Configuration			
Restricted Access Domains:			
Enable Web Admin Access:	yes 🔹	Admin Passwd:	
User Password:	****		
Miscellaneous Settings			
Syslog Server:		Debug Server:	
Debug Level:	0 -		
	Undo All Ch	anges Submit All Changes	
	ondoración		

После этого нажать Submit All Changes .

Во вкладке SIP (см. рисунок 2) необходимо прописать следующие параметры:

В разделе SIP Timer Values (sec):

Поле Reg Max Expires: выставляем значение 900

Поле Reg Retry Long Intvl: выставляем значение 600

В разделе RTP Parameters :

Поле RTP Port Min: выставляем значение 10000

Поле RTP Port Max: выставляем значение 20000

Поле RTP Packet Size: выставляем значение 0.010

LINKSYS [®] A Division of Cisco Systems, Inc.		Linksys Phone Adapter Configuration		
Router	Voice			
Info System SIP P	rovisioning Regional Lir	ne 1 Line 2 User 1 User 2	User Login basic advance	
SIP Parameters				
Max Forward:	70	Max Redirection:	5	
Max Auth:	2	SIP User Agent Name:	\$VERSION	
SIP Server Name:	\$VERSION	SIP Reg User Agent Name:		
SIP Accept Language:		DTMF Relay MIME Type:	application/dtmf-relay	
Hook Flash MIME Type:	application/hook-flash	Remove Last Reg:	no 💌	
Use Compact Header:	no 🗾	Escape Display Name:	no 💌	
RFC 2543 Call Hold:	yes 💌	Mark All AVT Packets:	yes 💌	
SIP Timer Values (sec)				
SIP T1:	.5	SIP T2:	4	
SIP T4:	5	SIP Timer B:	32	
SIP Timer F:	32	SIP Timer H:	32	
SIP Timer D:	32	SIP Timer J:	32	
INVITE Expires:	240	ReINVITE Expires:	30	
Reg Min Expires:	1	Reg Max Expires:	900	
Reg Retry Intvl:	30	Reg Retry Long Intvl:	600	
Response Status Code Ha	ndling			
SIT1 RSC:		SIT2 RSC:		
SIT3 RSC:		SIT4 RSC:		
Try Backup RSC:		Retry Reg RSC:		
RTP Parameters				
RTP Port Min:	10000	RTP Port Max:	20000	
RTP Packet Size:	0.010	Max RTP ICMP Err:	0	
RTCP Tx Interval:	0	No UDP Checksum:	no 💌	
Stats In BYE:	no 🔻		10	

Рисунок 2

После этого нажать Submit All Changes .

Во вкладке Regional (см. рисунок 3) В разделе Vertical Service Activation Codes значения всех полей должны быть удалены:

Interdigit Long Timer:	10	Interdigit Short Timer:	3	
CPC Delay:	2	CPC Duration:	0	
Vertical Service Activation Co	das			
Call Return Code:	ues	Call Redial Code:		
Blind Transfer Code:		Call Back Act Code:		_
Call Back Deact Code:		Call Back Busy Act Code:		_
Cfwd All Act Code:		Cfwd All Deact Code:		_
Cfwd Busy Act Code:	-	Cfwd Busy Deact Code:	-	_
Cfwd No Ans Act Code:		Cfwd No Ans Deact Code:		-
Cfwd Last Act Code:		Cfwd Last Deact Code:		
Block Last Act Code:		Block Last Deact Code:		
Accept Last Act Code:		Accept Last Deact Code:		-
CW Act Code:		CW Deact Code:		
CW Per Call Act Code:		CW Per Call Deact Code:		-
Block CID Act Code:		Block CID Deact Code:		-
Block CID Act Code:		Block CID Bes Call Deact Code:	-	
Block ANC Act Code:		Block ANC Deact Code:		-
DND Act Code:		DND Deact Code:		-
CID Act Code:		CID Deact Code:		_
CID Act Code:		CWCID Deact Code:		_
Dist Ding Act Code:		Dist Bing Deact Code:		
Encod Dial Act Code:		Secure All Call Act Code:		-
Speed Dial Act Code:		Secure All Call Act Code:		-
Secure No Call Act Code:		Conforance Act Code:		-
Atta Vias Act Code:		Medem Line Tendle Code:		-
Atth-Aler Act Code:		Modern Line Toggle Code:		
EAV Line Tecale Code:				
FAX Line Toggle Code:				
FAX Line Toggle Code: Referral Services Codes:				_
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes:				_
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme	nt Codes			
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number:	nt Codes			_
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes	nt Codes	N		
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes	nt Codes	ß		
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selectio	nt Codes : n Codes	\$		
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selectio Prefer G711u Code:	nt Codes : n Codes *017110	Force G711u Code:	*027110	
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selectio Prefer G711u Code: Prefer G711a Code:	nt Codes : n Codes *017110 *017111	Force G711u Code: Force G711a Code:	*027110 *027111	
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selection Prefer G711u Code: Prefer G711a Code: Prefer G723 Code:	nt Codes : n Codes *017110 *017111 *01723	Force G711u Code: Force G711a Code: Force G723 Code:	*027110 *027111 *02723	
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selectio Prefer G711u Code: Prefer G711a Code: Prefer G723 Code: Prefer G726r16 Code:	nt Codes : n Codes *017110 *017111 *01723 *0172616	Force G711u Code: Force G711a Code: Force G723 Code: Force G726r16 Code:	*027110 *027111 *02723 *0272616	
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selection Prefer G711u Code: Prefer G711a Code: Prefer G723 Code: Prefer G726r16 Code: Prefer G726r24 Code:	nt Codes *017110 *017111 *01723 *0172616 *0172624	Force G711u Code: Force G711a Code: Force G723 Code: Force G726r16 Code: Force G726r24 Code:	*027110 *027111 *02723 *0272616 *0272624	
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selectio Prefer G711u Code: Prefer G711a Code: Prefer G723 Code: Prefer G726r16 Code: Prefer G726r24 Code: Prefer G726r32 Code:	nt Codes *017110 *017111 *01723 *0172616 *0172624 *0172632	Force G711u Code: Force G711u Code: Force G711a Code: Force G723 Code: Force G726r16 Code: Force G726r24 Code: Force G726r32 Code:	*027110 *027111 *02723 *0272616 *0272624 *0272632	
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selectio Prefer G711u Code: Prefer G711a Code: Prefer G726r16 Code: Prefer G726r16 Code: Prefer G726r24 Code: Prefer G726r32 Code: Prefer G726r40 Code:	nt Codes *017110 *017111 *01723 *0172616 *0172624 *0172632 *0172640	Force G711u Code: Force G711u Code: Force G711a Code: Force G723 Code: Force G726r16 Code: Force G726r24 Code: Force G726r32 Code: Force G726r40 Code:	*027110 *027111 *02723 *0272616 *0272624 *0272632 *0272640	
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selectio Prefer G711u Code: Prefer G711a Code: Prefer G726r16 Code: Prefer G726r24 Code: Prefer G726r32 Code: Prefer G726r40 Code: Prefer G729a Code:	nt Codes *017110 *017111 *01723 *0172616 *0172624 *0172624 *0172640 *01729	Force G711u Code: Force G711u Code: Force G711a Code: Force G723 Code: Force G726r16 Code: Force G726r24 Code: Force G726r32 Code: Force G726r40 Code: Force G729a Code:	*027110 *027111 *02723 *0272616 *0272624 *0272632 *0272640 *02729	
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selectio Prefer G711u Code: Prefer G711a Code: Prefer G723 Code: Prefer G726r16 Code: Prefer G726r24 Code: Prefer G726r32 Code: Prefer G726r40 Code: Prefer G729a Code:	nt Codes *017110 *017111 *01723 *0172616 *0172632 *0172640 *01729	Force G711u Code: Force G711u Code: Force G711a Code: Force G723 Code: Force G726r16 Code: Force G726r24 Code: Force G726r32 Code: Force G726r40 Code: Force G729a Code:	*027110 *027111 *02723 *0272616 *0272624 *0272632 *0272640 *02729	
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selectio Prefer G711u Code: Prefer G711a Code: Prefer G726r16 Code: Prefer G726r24 Code: Prefer G726r24 Code: Prefer G726r32 Code: Prefer G726r40 Code: Prefer G729a Code: Prefer G729a Code:	nt Codes *017110 *017111 *01723 *0172616 *0172624 *0172632 *0172640 *01729	Force G711u Code: Force G711u Code: Force G711a Code: Force G723 Code: Force G726r16 Code: Force G726r24 Code: Force G726r32 Code: Force G726r40 Code: Force G729a Code:	*027110 *027111 *02723 *0272616 *0272624 *0272632 *0272640 *02729	
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selectio Prefer G711u Code: Prefer G711a Code: Prefer G726r16 Code: Prefer G726r16 Code: Prefer G726r24 Code: Prefer G726r32 Code: Prefer G726r40 Code: Prefer G729a Code: Prefer G729a Code:	nt Codes *017110 *017111 *01723 *0172616 *0172624 *0172632 *0172640 *01729	Force G711u Code: Force G711u Code: Force G711a Code: Force G723 Code: Force G726r16 Code: Force G726r24 Code: Force G726r32 Code: Force G726r40 Code: Force G729a Code: Set Local Time (HH/mm):	*027110 *027111 *02723 *0272616 *0272624 *0272632 *0272640 *02729	
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selection Prefer G711u Code: Prefer G711a Code: Prefer G726r16 Code: Prefer G726r26 Code: Prefer G726r24 Code: Prefer G726r32 Code: Prefer G726r40 Code: Prefer G729a Code: Miscellaneous Set Local Date (mm/dd): Time Zone:	nt Codes *017110 *017111 *01723 *0172616 *0172624 *0172632 *0172640 *01729	Force G711u Code: Force G711u Code: Force G711a Code: Force G723 Code: Force G726r16 Code: Force G726r24 Code: Force G726r32 Code: Force G726r40 Code: Force G729a Code: Set Local Time (HH/mm): FXS Port Impedance:	*027110 *027111 *02723 *0272616 *0272632 *0272632 *0272640 *02729	
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selection Prefer G711u Code: Prefer G711a Code: Prefer G726r16 Code: Prefer G726r26 Code: Prefer G726r24 Code: Prefer G726r32 Code: Prefer G726r40 Code: Prefer G729a Code: Miscellaneous Set Local Date (mm/dd): Time Zone: Daylight Saving Time Rule:	nt Codes *017110 *017111 *01723 *0172616 *0172624 *0172632 *0172640 *01729 GMT-08:00 start=4/1/7;end=10/-1/7;si	Force G711u Code: Force G711a Code: Force G711a Code: Force G723 Code: Force G726r16 Code: Force G726r24 Code: Force G726r24 Code: Force G726r32 Code: Force G726r40 Code: Force G729a Code: Set Local Time (HH/mm): FXS Port Impedance: ave=1	*027110 *027111 *02723 *0272616 *0272624 *0272632 *0272640 *02729	
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selection Prefer G711u Code: Prefer G711a Code: Prefer G723 Code: Prefer G726r16 Code: Prefer G726r24 Code: Prefer G726r32 Code: Prefer G726r40 Code: Prefer G726r40 Code: Prefer G729a Code: Miscellaneous Set Local Date (mm/dd): Time Zone: Daylight Saving Time Rule: FXS Port Input Gain:	nt Codes *017110 *017111 *01723 *0172616 *0172624 *0172632 *0172640 *01729 GMT-08:00 GMT-08:00 Start=4/1/7;end=10/-1/7;si -3	Force G711u Code: Force G711a Code: Force G711a Code: Force G723 Code: Force G726r16 Code: Force G726r24 Code: Force G726r32 Code: Force G726r40 Code: Force G729a Code: Set Local Time (HH/mm): FXS Port Impedance: ave=1 FXS Port Output Gain:	*027110 *027111 *02723 *0272616 *0272624 *0272632 *0272640 *02729	
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selection Prefer G711u Code: Prefer G711a Code: Prefer G726r16 Code: Prefer G726r24 Code: Prefer G726r32 Code: Prefer G726r32 Code: Prefer G726r40 Code: Prefer G729a Code: Prefer G729a Code: Miscellaneous Set Local Date (mm/dd): Time Zone: Daylight Saving Time Rule: FXS Port Input Gain: DTMF Playback Level:	nt Codes *017110 *017111 *01723 *0172616 *0172624 *0172632 *0172640 *01729 GMT-08:00 start=4/1/7;end=10/-1/7;si -3 -16	Force G711u Code: Force G711a Code: Force G711a Code: Force G723 Code: Force G726r16 Code: Force G726r24 Code: Force G726r32 Code: Force G726r40 Code: Force G729a Code: Set Local Time (HH/mm): FXS Port Impedance: ave=1 FXS Port Output Gain: DTMF Playback Length:	*027110 *027111 *02723 *0272616 *0272624 *0272624 *0272632 *0272640 *02729	
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selection Prefer G711u Code: Prefer G711a Code: Prefer G726r16 Code: Prefer G726r24 Code: Prefer G726r24 Code: Prefer G726r32 Code: Prefer G726r40 Code: Prefer G729a Code: Prefer G729a Code: Set Local Date (mm/dd): Time Zone: Daylight Saving Time Rule: FXS Port Input Gain: DTMF Playback Level: Detect ABCD:	nt Codes *017110 *017111 *01723 *0172616 *0172624 *0172632 *0172640 *01729 GMT-08:00 start=4/1/7;end=10/-1/7;si -3 -16 yes Codes	Force G711u Code: Force G711u Code: Force G711a Code: Force G723 Code: Force G726r16 Code: Force G726r24 Code: Force G726r32 Code: Force G726r40 Code: Force G729a Code: Force G729a Code: Set Local Time (HH/mm): FXS Port Impedance: ave=1 FXS Port Output Gain: DTMF Playback Length: Playback ABCD:	*027110 *027111 *02723 *0272616 *0272624 *0272632 *0272640 *02729 600	
FAX Line Toggle Code: Referral Services Codes: Feature Dial Services Codes: Vertical Service Announceme Service Annc Base Number: Service Annc Extension Codes Outbound Call Codec Selection Prefer G711u Code: Prefer G711a Code: Prefer G726r16 Code: Prefer G726r26 Code: Prefer G726r24 Code: Prefer G726r32 Code: Prefer G726r40 Code: Prefer G729a Code: Miscellaneous Set Local Date (mm/dd): Time Zone: Daylight Saving Time Rule: FXS Port Input Gain: DTMF Playback Level: Detect ABCD: Caller ID Method:	nt Codes *017110 *017111 *01723 *0172616 *0172624 *0172632 *0172640 *01729 GMT-08:00 start=4/1/7;end=10/-1/7;si -3 -16 yes Bellcore(N.Amer,China) Start = 4	Force G711u Code: Force G711a Code: Force G711a Code: Force G723 Code: Force G726r16 Code: Force G726r24 Code: Force G726r32 Code: Force G726r40 Code: Force G729a Code: Set Local Time (HH/mm): FXS Port Impedance: ave=1 FXS Port Output Gain: DTMF Playback Length: Playback ABCD: Caller ID FSK Standard:	*027110 *027111 *02723 *0272616 *0272624 *0272632 *0272640 *02729 600 • -3 .1 yes • bell 202 •	

Рисунок 3.

После этого нажать Submit All Changes .

Во вкладке Line1 в разделе Network Settings (см. рисунок 4):

Поле Jitter Buffer Adjustment: выставляем значение disable

В разделе Proxy and Registration :

Поле Proxy: выставляем IP адрес 83.243.65.2

Поле Register Expires: выставляем значение 600

Поле Make Call Without Reg: выставляем значение yes

Поле Ans Call Without Reg: выставляем значение yes

В разделе Subscriber Information (см.рисунок 5) на примере номера 602-26-57 :

Поле Display Name: выставляем значение 6022657

Поле User ID: выставляем значение 78126022657

Поле Password: здесь необходимо прописать пароль для регистрации номера, который прописан в договоре.

Поле Use Auth ID: выставляем значение yes

Поле Auth ID:: выставляем значение 78126022657

В разделе Supplementary Service Subscription

Поле Call Waiting Serv: выставляем значение no

В разделе Audio Configuration

Поле Preferred Codec: выставляем значение G711a

Поле Use Pref Codec Only: выставляем значение yes

Поле G729a Enable: выставляем значение no

Поле G723 Enable: выставляем значение no

Поле G726-16 Enable: выставляем значение no

Поле G726-24 Enable: выставляем значение no

Поле G726-32 Enable: выставляем значение no

Поле G726-40 Enable: выставляем значение no

Поле FAX Passthru Codec: выставляем значение G711a

Поле FAX Enable T38: выставляем значение yes



A Division of Cisco Systems, Inc.

Linksys Phone Adapter Configuration

Router	Voice				
Info System SIP	Provisioning Reg	jional Line	1 Line 2 User 1 Use	er 2 User Login ba	<u>isic</u> advanced
Line Enable:	yes 📩				
Streaming Audio Server	(SAS)				
SAS Enable:	no 🕶		SAS DLG Refresh Intvl:	30	
SAS Inbound RTP Sink:					
NAT Settings					
NAT Mapping Enable:	no 💌		NAT Keep Alive Enable:	no 🔻	
NAT Keep Alive Msg:	\$NOTIFY		NAT Keep Alive Dest:	\$PROXY	
Notwork Cottings					
SIP ToS /DiffSery Value:	0×68		SID CoS Value:	3 [0-7]	
BTP ToS/DiffServ Value:	0x68		RTP CoS Value:	6 [0-7]	
Network Jitter Level:	high	-	Jitter Buffer Adjustment:	disable •	
	-	-			
SIP Settings					
SIP Port:	5060		SIP 100REL Enable:	no 🗾	
EXT SIP Port:			Auth Resync-Reboot:	yes 🗾	
SIP Proxy-Require:			SIP Remote-Party-ID:	yes 📩	
SIP GUID:	no 📩		SIP Debug Option:	none	<u> </u>
RTP Log Intvl:	0		Restrict Source IP:	no 🗾	
Referor Bye Delay:	4		Refer Target Bye Delay:	0	
Referee Bye Delay:	0		Refer-To Target Contact:	no 💌	
Sticky 183:	no 🗾				
Call Feature Settings					
Blind Attn-Xfer Enable:	no 💌		MOH Server:		
Xfer When Hangup Conf:	yes 🗾		Conference Bridge URL:		
Conference Bridge Ports	3 🗾				
Proxy and Registration					
Proxy:	83.243.65.2				
Outbound Proxy:				9. 19	
Use Outbound Proxy:	no 📩		Use OB Proxy In Dialog:	yes 💌	
Register:	yes 💌		Make Call Without Reg:	yes 🔳	
Register Expires:	600		Ans Call Without Reg:	yes 📲	
Use DNS SRV:	no 💌		DNS SRV Auto Prefix:	no 💌	
Proxy Fallback Intvl:	3600		Proxy Redundancy Method	I: Normal	1
Voice Mail Server:			Mailbox Subscribe Expires	: 2147483647	
Subscriber Information					
Display Name:	6022657		User ID:	78126022657	
Password:	******		Use Auth ID:	yes 💌	
Auth ID:	78126022657				

Рисунок 4.

Proxy Fallback Intvl:	3600	Proxy Redundancy Method:	Normal 🗾
Voice Mail Server:		Mailbox Subscribe Expires:	2147483647
Subscriber Information			
Display Name:	6022657	User ID:	78126022657
Password:	****	Use Auth ID:	yes 📩
Auth ID:	78126022657		
Mini Certificate:			
SRTP Private Key:			
Supplementary Service Sul	bscription		
Call Waiting Serv:	no 🗾	Block CID Serv:	yes 💌
Block ANC Serv:	yes 🗾	Dist Ring Serv:	yes 🗾
Cfwd All Serv:	yes 📩	Cfwd Busy Serv:	yes 📩
Cfwd No Ans Serv:	yes 💌	Cfwd Sel Serv:	yes 💌
Cfwd Last Serv:	yes 💌	Block Last Serv:	yes 💌
Accept Last Serv:	yes 💌	DND Serv:	yes 💌
CID Serv:	yes 📕	CWCID Serv:	yes 🗾
Call Return Serv:	yes 🔹	Call Redial Serv:	yes 🕶
Call Back Serv:	yes 💌	Three Way Call Serv:	yes 💌
Three Way Conf Serv:	yes 🔹	Attn Transfer Serv:	yes 🔳
Unattn Transfer Serv:	yes 🕶	MWI Serv:	yes 💙
VMWI Serv:	ves •	Speed Dial Serv:	ves •
Secure Call Serv:	ves •	Referral Serv:	ves 🔻
Feature Dial Serv:	ves T	Service Announcement Serv:	no 🔹
Audio Configuration			
Preferred Codec:	G711a 🗾	Silence Supp Enable:	no 📩
Use Pref Codec Only:	yes 💌	Silence Threshold:	medium 📩
G729a Enable:	no 📩	Echo Canc Enable:	yes 💌
G723 Enable:	no 📩	Echo Canc Adapt Enable:	yes 📩
G726-16 Enable:	no 💌	Echo Supp Enable:	yes 💌
G726-24 Enable:	no 💌	FAX CED Detect Enable:	yes 💌
G726-32 Enable:	no 🔹	FAX CNG Detect Enable:	yes 🕶
G726-40 Enable:	no 🔹	FAX Passthru Codec:	G711a 🔻
DTMF Process INFO:	yes 🔹	FAX Codec Symmetric:	yes *
DTMF Process AVT:	yes 🔹	FAX Passthru Method:	NSE *
DTMF Tx Method:	Auto -	FAX Process NSE:	yes 🕶
Hook Flash Tx Method:	None -	FAX Disable ECAN:	no 🔹
Release Unused Codec:	ves T	FAX Enable T38:	ves T
FAX T38 Redundancy:	1	FAX Tone Detect Mode:	caller or callee
Dial Plan			
	(*xx [3469]11 0 00 [2	-9]xxxxxx 1xxx[2-9]xxxxxxS0 xxx	(XXXXXXXXX)
Dial Plan:		and the second s	32-
Dial Plan: Enable IP Dialing:	no 🕇	Emergency Number:	
Dial Plan: Enable IP Dialing:	no 📩	Emergency Number:	
Dial Plan: Enable IP Dialing: FXS Port Polarity Configura	no I	Emergency Number:	
Dial Plan: Enable IP Dialing: FXS Port Polarity Configura Idle Polarity:	tion Forward	Emergency Number: Caller Conn Polarity:	Forward 🔻
Dial Plan: Enable IP Dialing: FXS Port Polarity Configura Idle Polarity: Callee Conn Polarity:	tion Forward	Emergency Number: Caller Conn Polarity:	Forward 🗾

Copyright © 1992-2006 Cisco Systems, Inc. All Rights Reserved.

Рисунок 5.

После этого нажать Submit All Changes .